




Recessed Downlight Installation Instructions



Package Content



Parts	Description	Quantity
A	4/6/8/10 INCH 5CCT LED Selectable LED Commercial Downlight	1
B	Hole cutout card	1
C	Wire nuts	5

Dimming Information

This recessed downlight is suitable for use in dimming circuits. For 100% to 10% light control, use with an LED compatible dimmer.

LUTRON	RMJS-8T-DV-B, Diva DVSTV, MS-Z101-WH, DVSTV-WH	LEGRAND	RH4FBL3PW
---------------	--	----------------	-----------

⚠ Warning

PLEASE READ ALL INSTRUCTIONS BEFORE ATTEMPTING INSTALLATION

To avoid electric shock, disconnect power at source prior to installation

- Before installation, please carefully check whether the fixture is damaged, and contact the supplier in time if there is any damage.
- To prevent personal injury or product damage only licensed electricians should install.
- To avoid electric shock or component damage disconnect power before attempting installation or servicing.
- This product must be installed in accordance with the national electric code (NEC) and all applicable federal, state and local electric codes and safety standards.
- Disconnect product and allow cooling prior to servicing.
- Any alteration or modification of this product is expressly forbidden as it may cause serious personal injury, death, property damage and/or product malfunction.
- To prevent product malfunction and/or electrical shock this product must be properly grounded.
- This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
- Min 75°C supply conductor
- CONSULT A QUALIFIED ELECTRICIAN TO ENSURE CORRECT BRANCH CIRCUIT CONDUCTOR.
- CAUTION - RISK OF FIRE.
- This product is not available for several special environments, such as places with corrosive gas liquids or high pressure water vapor.

Installation Instructions

1: Turn off the power before installation. Remove the existing fixture if applicable. Determine the location and necessary hole cutout diameter using the supplied table and cut the ceiling hole with the listed approximate diameter, see Fig1.

2: Choose desired CCT & Wattage by simply switching the switch, see Fig2.

Recessed Downlight Installation Instructions



3: Attach the carabiner safety clip to the existing fixture housing ,see Fig3.

4: Connect AC and dimming supply cables inside the hardwire Junction Box(not included) by using 5 wire nuts in the following manner: black to black, white to white, pink to pink or grey, purple to purple, and green-earth to ground wire, see Fig4.

5: Push the downlight spring loaded clips upwards and insert the base into the mounting hole. Release the clips and the fixture will grip flush with the ceiling/drywall, see Fig5.

6: Turn on the power to confirm the fixture is working properly, see Fig6.

HOLE SIZE

4inch:4 21/64"(110mm)
 6inch:6 19/64" (160mm)
 8inch:8 5/64"(205mm)
 10inch:8 31/32"(228mm)

Fig1

Selectable Wattage

4inch:6W-9W-12W
 6inch:12W-17W-22W
 8inch:17W-24W-30W
 32W-42W-52W
 10inch:22W-30W-38W

Selectable CCT

- 2700K
- 3000K
- 3500K
- 4000K
- 5000K

Fig2

