



Description

Allows for easy replacement of existing Fluorescent, incandescent, halogen and xenon under cabinet lighting. Built-in driver, captive screws and knockouts for easy installation in new work or remodel applications.

Features

- TBuilt-in integral electronic driver
- Dimmable 120V
- On / Off rocker switch
- ≥80 or ≥90 CRI
- Available in 9 different lengths
- Rear panel punch-in electrical connectors for easy wiring
- 2700K available
- 50,000 hour life expectancy
- Finish: White
- Linkable up to 400W
- Certified to CEC under Title 20 regulations.



Link several undercabinets together with the Linkable Connector Wire



Pre-positioned installation screws

Undercabinet Included Accessories



Captive Screws (pre-installed on each fixture)



Plastic Washers



Wire Connectors



End-to-End Connectors



Rocker Switch



3/4" Diecast Connector

Undercabinet Available Accessories



Power Cords



Linkable Connector with Wire (available in four lengths)



Project Name	
Catalog #	
Job Type	
Prepared By	
Notes	

Fixture Ordering Information

Model	Dimension	Wattage	Lumen	Voltage	CRI
LL-LEDUC8	8" x 3½"	4	250	120V	≥90
LL-LEDUC11	11" x 3½"	6	360	120V	≥90
LL-LEDUC14	14" x 3½"	9	510	120V	≥90
LL-LEDUC18	18" x 3½"	11	620	120V	≥90
LL-LEDUC22	22" x 3½"	11	680	120V	≥90
LL-LEDUC29	29" x 3½"	13	780	120V	≥90
LL-LEDUC32	32" x 3½"	15	950	120V	≥90
LL-LEDUC36	36" x 3½"	16	1060	120V	≥90
LL-LEDUC48	48" x 3½"	18	1180	120V	≥90

Accessories Ordering Information

Part Number	Description
LL-LEDCN1IN	Linkable Connector 1 in (25mm)
LL-LEDCN2IN	Linkable Connector 2 in (51mm)
LL-LEDCN3IN	Linkable Connector 3 in (76mm)
LLL-EDCN2FT	Linkable Connector 1 ft (610mm)
LL-LEDJBOX	J-Box With 2 Female Connectors
LL-LEDPC	Power Cord