


Flood Light Small Installation Instructions



⚠ Warning


1. To avoid electric shock, disconnect power at source prior to installation.
2. The installation should be performed by qualified electricians or lighting technicians.
3. This product must be installed in accordance with the national electric code (NEC) and all applicable federal, state and local electric codes and safety standards.
4. Disconnect product and allow cooling prior to servicing.
5. Any alteration or modification of this product is expressly forbidden as it may cause serious personal injury, death, property damage and/or product malfunction.
6. To prevent product malfunction and/or electrical shock this product must be properly grounded.
7. Suitable for operation in ambient temperatures ranging from -40°C to 45°C.
8. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

1/2" Knuckle Mount Installation



1. Mount this fixture to any metal 1/2" NPS threaded mounting (supplied by others) , please mount the fixture prior to make wiring connection.
2. Route electrical leads through the mounting hole.
3. Seal knuckle threads with sealing compound (provided by others). Secure the mounting fitter to fixture with lock nut.
4. Make wire connection (see wiring diagram above).
5. Adjust aiming angle of the fixture by loosening the pivot screw. Use visual angle indicators to set desired angle, then tighten pivot screw.

Trunnion Mount Installation



1. Fix trunnion on the wall by screws.
2. Wire Live and Neutral Cable respectively. Watch out for joint point and screw them well in case of electric leakage.
3. Adjust light by loosening screws to achieve different installation angle.
4. Waterproof measurement are necessary when connecting to external power supply cord.

Troubleshooting


1. Check that the line voltage at the fixture is correct. Refer to wiring diagram above.
2. Is the fixture grounded properly?
3. Be sure the photocell, if used, is functioning properly.

Flood Light Small Installation Instructions



Wiring Diagram

For 0-10V Dimming Version, please refer to wiring diagram below.



Troubleshooting

1. Check that the line voltage at the fixture is correct. Refer to wiring diagram above.
2. Is the fixture grounded properly?
3. Be sure the photocell, if used, is functioning properly.